au by KDDI

Basic Manual

NS02

Introduction

Thank you for purchasing the NS02. Before using your NS02, be sure to read the NS02 Basic Manual (this PDF manual) to ensure correct usage. After you have finished reading this manual, store this PDF manual and the printed manuals in safe places so you can retrieve them whenever you need them.

Manuals for the NS02

The NS02 comes with the Basic Manual and Instruction Manual.

● **For learning the basics:**

Read the NS02 Basic Manual (this manual).

● **For learning details on using each function:**

Read the supplied NS02 Instruction Manual (Japanese). Be sure to read the Safety Precautions “安全上のご注意” to ensure proper usage of the NS02.

The keyword searchable au Online Manual is also available on the au homepage:
http://www.au.kddi.com/manual/index.html


- To access from EZweb: EZ ⇒ *au one Top* ⇒ *auお客さまサポート* (au Customer Support) ⇒ *オンラインマニュアル* (Online Manual)

Scan this QR code to access the au Online Manual. ▶

Illustrations and Screenshots in This Manual

Note on Illustrations

The illustrations in this manual may look different from the actual cell phone in shape, color and typeface. The key illustrations are also simplified as shown below.



	Key Illustration
①	
②	
③	ペア
④	1 2 3 4 5 6 7 8 9 * 0 #
⑤	
⑥	
⑦	
⑧	電源
⑨	Clear/メモ

Note on Screenshots

The screenshots in this manual are simplified and may look different from the actual cell phone screens.

- The display design themes of the NS02 vary by model color. The screenshots for the Black models are used in this manual.

Notes on Cell Phone Use

Cell Phone Etiquette

The cell phone always emits weak radio waves when power is on.
Use the cell phone in an enjoyable and safe manner without forgetting to be considerate of others around you.

● Use of cell phones is not allowed in some places.
- Do not use the cell phone while you are driving. Doing so is both dangerous and prohibited by law.
- Using a cell phone in an aircraft is prohibited by law. Be sure to turn the cell phone off.

● Radio waves from cell phones may interfere with medical electrical equipment.
- Some people close to you in crowded places such as packed trains may be using a cardiac pacemaker. Turn the cell phone off in such places.
- Abide by the rules of hospitals and other medical institutions where it is forbidden to use or carry cell phones.

● Be considerate of where you use the cell phone and how loudly you talk.
- Do not make calls in theaters, museums, libraries, and other similar places. Turn power off or turn on manner mode not to disturb others around you by ring tones.
- Do not use the cell phone on a street where you might interrupt the flow of pedestrians.
- Move to areas where you will not inconvenience others on trains or in hotel lobbies.
- Refrain from talking in a loud voice.
- Obtain the permission of other people before you take their photos with the cell phone's camera.
- Do not record information with the cell phone's camera in bookstores and other locations where taking photos is not permitted.

Do not use the cell phone while driving!

Turn off your cell phone or put it in Drive Mode while driving.

Do not use the cell phone while driving a car/motorcycle or riding a bicycle. It may result in a traffic accident. Using a cell phone while driving is prohibited by law. Using a cell phone while riding a bicycle may also be punishable by law.

Prohibited!
- Looking at a cell phone display
- Talking on a cell phone while holding it

Drive Mode

In Drive Mode, a Japanese message meaning "I'm driving now, so I can't answer your call." is played when a call is received, and asks the caller to leave a message on the easy voice memo.

When the standby screen is displayed, press ⦿ ⇒ *Tools* ⇒ *Manner Mode* ⇒ *Drive Mode*.

Disaster Message Board Service

When a big scale disaster occurs, you can register your safety information from EZweb. The registered information can be referred from anywhere in Japan from EZweb or Internet.

Registering safety information	• When a big scale disaster occurs, from an au phone, you can register your safety information (i.e. your condition and comments) to the 災害用伝言板 (Disaster Message Board) created on the EZweb. • After registration of your safety information, e-mail is sent to your family or acquaintances you have previously designated to notify that your safety information has been uploaded to the 災害用伝言板 (Disaster Message Board).
Inquiring for safety information	• You can inquire for safety information of a person by entering his/her phone number from EZweb or Internet.* * To inquire from other carriers' cell phone, a PHS or PC, access "http://dengon.ezweb.ne.jp/".

Access	[E] ⇒ *au one Top* ⇒ *災害用伝言板* (Disaster Message Board)
	http://dengon.ezweb.ne.jp/

- The maximum storage period of the registered information is 72 hours.
- The maximum available number of registrations is 10 per phone number. When the number of registrations exceeds 10, the oldest one is overwritten.
- The demonstration of this service can be referred to anytime by pressing [E] ⇒ *au one Top* ⇒ *auお客さまサポート* (au Customer Support) ⇒ *調べる* (Search) ⇒ *災害用伝言板（デモ版）* (Disaster Message Board (Demo Version)).
- To view the Disaster Message Board in English, select *English* from the top menu of the Disaster Message Board.


Contents

Getting Ready


Checking the Contents of the Box

The box contains the cell phone and accessories.

- Cell phone



- Battery pack



- Pantech external terminal conversion adapter 02




- CD-ROM
- Instruction Manual (Japanese)
- Warranty (Japanese)
- Safety Precautions (Japanese)
- Safety Precautions about Adapters (Japanese)
- JIBUN BANK Launcher Operation Guide (Japanese)


- Desktop holder, AC adapter and microSD memory card are not included. Purchase the desktop holder (sold separately) and the common AC adapter 01/02 (sold separately) and a commercially available microSD memory card.

Names of Parts

From the Front




From the Back



* Do not remove this card unnecessarily as your phone number is recorded on it.


From the Sides



Charging the Battery Pack

The battery pack is not fully charged at the time of purchase. Be sure to charge the battery pack before using the cell phone for the first time.

- The desktop holder and the AC adapter is not included. Purchase the desktop holder (sold separately) and the common AC adapter 01/02 (sold separately).



➡ **Connect the common AC adapter 01/02 to the desktop holder.**

- Check the shape of the connector of the common AC adapter 01/02 and then plug it straight into the power terminal of the desktop holder.

➡ **Unfold the power plug of the common AC adapter 01/02 and plug it into a 100 V AC power outlet.**

➡ **Close the cell phone with the battery pack attached and insert it into the desktop holder as shown in the figure.**


➡ **Confirm that the charging indicator lights.**

- Charging: The charging indicator lights.
- Charging finished: The charging indicator goes out.

- Hold the desktop holder while removing the cell phone.
- You can also charge the battery pack by connecting the Pantech external terminal conversion adapter 02 and the common AC adapter 01/02 directly to the external power terminal.

Learning the Basics

Key Assignments



- (Left) : Display Incoming History.
- (Down) : Display Alert window/Shortcut menu.
- [電話帳] : Use Phone Book.
- [メール] : Send/receive e-mail/c-mail.
- [ペア] : Make/answer calls. Use the Pair function.
- [Clear/メモ] : Set/cancel Easy voice memo. Delete characters. Cancel operation.
- [0] ~ [9] [*] [#] : Input phone numbers and characters.
- [*] : Set/cancel Manner mode.
- (Up) : Display the ticker field, info pane.
- (Right) : Display Outgoing History.
- (Center) : Display Main menu.
- [アプリ] : Activate EZapps.
- [EZweb] : Display EZ Service menu.
- [電源] : Turn power on/off. End call/communication. Cancel operation.
- [#] : Turn Pocket light on.
- [0] : Sound Safety buzzer.

- If you lose track of where you are or if you make a mistake, press [Clear/メモ] to return to the previous screen. Return to the standby screen by pressing [電源].

Hiding/Redisplaying the Alert Window

When the alert window is displayed on the standby screen, you can temporarily hide it by pressing [Clear/メモ] and then display the Main menu by pressing ◉. To redisplay the hidden alert window, press ◯ when the standby screen is displayed.

Alert window



Turning On Power

Hold down [電源] for at least one second.

- You cannot receive or make calls if [圏外] (out of range indicator) is displayed.

Turning Off Power

When the standby screen is displayed, hold down [電源] for at least two second.

Switching the Display Language to English

You can switch the display language for function names and other items to English.

When the standby screen is displayed, press ◉.

➡ **Use ◈ to select *機能設定* (Settings) and then press ◉ (選択 [Select]).**

➡ **Use ◈ to select *画面表示* (Screen Setup) and then press ◉ (選択 [Select]).**

➡ **Use ◈ to select *Set Language* and then press ◉ (選択 [Select]).**

➡ **Use ◈ to select *English* and then press ◉ (OK).**

Initial Setup of E-mail and EZweb

To use e-mail and EZweb, you need to apply for an EZweb subscription. If you did not apply for an EZweb subscription at the time of purchase, contact an au shop or the au Customer Service Center.
Also, before use, you need to configure initial settings. Your e-mail address is assigned automatically in the initial setup.

When the standby screen is displayed, press [✉].

➡ **Press ◉ (OK).**
After a short while, your e-mail address is displayed.

➡ **Press ◉ (OK).**
The initial settings are complete.

- You can also configure initial settings by pressing [EZ] or [A].


Checking Your Phone Number and E-mail Address

When the standby screen is displayed, press ◉ and then [O].

Display Indicators

Display indicators inform you of mail arrival, current settings, etc.

Display



Indicator		Description
①		Signal strength
②		Battery level
③		microSD memory card (commercially available) inserted
④		During a call
		Connecting to EZweb
⑤		EZapps activated
		Connecting over SSL
⑥		Missed calls
⑦		Receiving EZ News Flash information
⑧		New or unread e-mail/ c-mail
		New or unread emergency earthquake bulletin
⑨		Displaying secret informations

Indicator		Description
⑩		Movable to next/ previous screen
		Scrollable
⑪	2/20[金] 2:02	Current date and time
⑫		Easy voice memo set
⑬		Manner mode set
⑭		Alarm set
⑮		Schedule alarm set
⑯		Signal off mode set
⑰	USB	USB connected
⑱	S	Ring tone off
⑲	V	Vibrator on
⑳		Auto lock activated
㉑	—	Ticker field
㉒	—	Wallpaper
㉓	—	Info pane
㉔	—	Alert icon
㉕	—	Shortcut menu

- The date and time are set automatically.

Using Main Menu


You can access various functions from the Main menu.
The Main menu patterns vary by model color. The screenshots for the Black models are used in this manual.

Model Color	Main Menu Pattern
Black	Keitai-Arrange File1
Green	Keitai-Arrange File2
Ivory	Keitai-Arrange File3

You can use the Kantan menu by changing to the Kantan mode.


When the standby screen is displayed, press ◉, use ✥ to select *Kantan*, and then press ◉ (Select).

Each Main menu pattern has a different set of items.

Normal Menu	Kantan Menu
	
IrDA	Call
Photo	Camera
micro SD	microSD
JIBUN BANK	EZ Service
Data Folder	Data Folder
Tools	Tools
Memo	Memo
Alarm	Settings
Calendar	JIBUN BANK
Calculator	
Settings	
Kantan	

Changing Your E-mail Address

You can change the account name of your e-mail address.



When the standby screen is displayed, press ✉.

➡ **Use to select *E-Mail Setup* and then press ◉ (Select).**

➡ **Use to select *Other Setup* and then press ◉ (Select).**

The cell phone connects to the server.

➡ **Use to select *Eメールアドレスの変更* (Change E-mail Address) and then press ◉ (Select).**

➡ **Use to select the entry box, press ◉ (Edit), enter your security code, and then press ◉ (OK).**

- Your security code is the four-digit number you wrote on your subscription form.
- If the security code is incorrectly entered three times consecutively during a single day, the e-mail address change operation will be disabled until the next day.

➡ **Use to select *送信* (Send) and then press ◉ (Select).**

➡ **Use to select *承諾する* (Accept) and then press ◉ (Select).**

➡ **Use to select the entry box, press ◉ (Edit), enter an e-mail address using single-byte alphanumeric characters, and then press ◉ (OK).**

- For details on entering e-mail addresses, see page 21.

➡ **Use to select *送信* (Send) and then press ◉ (Select).**

➡ **Use to select *OK*, press ◉ (Select) and then ◉ (OK).**

- Check that the e-mail address has been updated before pressing ◉ (OK).

- Your e-mail address cannot be changed if the new address you enter in the above procedure is already being used. In this case, enter a different e-mail address.

Security Code and Passwords

You can use a security code and other passwords described below.
Take care not to forget your security code and passwords, because they are required for performing various operations and using subscription services.

Security Code

Usage Example	①Using the Answering Service (Voice Mail) and Call Transfer remotely from a fixed-line phone ②Making inquiries, applications, and changes while using au Customer Service Center voice guidance, au web pages, and EZweb ③Changing the settings of *Mail Filter* or *Other Setup* under E-Mail Setup
Initial Setting	The four-digit number you wrote on your subscription form

Lock No.

Usage Example	Changing various settings of the cell phone
Initial Setting	1234

EZ Password

Usage Example	Subscribing or canceling subscriptions to EZweb fee-based contents
Initial Setting	The four-digit number you wrote on your subscription form

Premium EZ Password

Usage Example	①Subscribing or canceling subscriptions to EZweb fee-based contents paid by *まとめてau支払い*(au Collective Payment Service) ②Purchasing products from EZweb sites using *まとめてau支払い*(au Collective Payment Service)
Initial Setting	The four-digit number you wrote on your subscription form

Making and Answering Calls

Making a Call

When the standby screen is displayed, use [0] to [9] to enter a phone number.

- When calling to a fixed-line phone, you also need to enter the area code.

➡ **Press [ペア].**

- To end the call, press [電源].

- After you enter a phone number, you can add 184 or 186 to the phone number as follows:
  ➡ Press ⦿ (Call).
  ➡ Use ⦿ to select *184 + Call* or *186 + Call* and then press ⦿ (Select).
  ➡ Press ⦿ (Call).
  ➡ Press ⦿ (Select).
  184 + Call: When you do not want to inform the other party of your phone number.
  186 + Call: When you want to inform the other party of your phone number.

Making an International Call

au International Call Service

Available without any additional application
Example: To call 212-123-△△△△ in the USA

Press [0] [0] [5] [3] [4] [5].
↑ International access code

➡ **Press [1].**
↑ Country code (USA)

➡ **Press [2] [1] [2].**
↑ Area code

➡ **Press [1] [2] [3] △△△△.**
↑ Phone number

➡ **Press [ペア].**

- Calling charges for this service are added to monthly cell phone calling charges and billed together.
- Check the country code at the au Customer Service Center.
- For charges, refer to au MOBILE PHONE SERVICE GUIDE or au Customer Service Center.

001 KOKUSAI MOBILE TALK

Application required.
For inquiries, contact the KDDI Customer Service Center.

フリーコール 0077-7160
(toll-free; open 9:00 to 20:00 everyday including weekends and national holidays)

001 – 010 – 1 – 212 – 123–XXXX

- 001: KDDI international access code
- 1: Country code (USA)
- 212: Area code
- 123–XXXX: Phone number

- Charges for 001 KOKUSAI MOBILE TALK are charged separately from monthly au telephone charges.
- Check the country code at the au Customer Service Center.
- For charges, refer to au MOBILE PHONE SERVICE GUIDE or au Customer Service Center.

Answering a Call

To answer a call, press [ペア].

- To end the call, press [電源].

Display When a Call is Received

The phone number of the caller appears.
If the caller's phone number and name are in the phone book, the name is also displayed.
When the phone number of the caller is not displayed, one of the following indicators may appear.

Indicator	Meaning
ID Unsent	The caller did not send a Caller ID.
Payphone	The call is from a pay phone.
Not Support	The call is from a phone that does not support Caller ID.

Missed Call Notification

If you did not answer a call, [missed call icon] and *Missed Call* are displayed to let you know that you missed a call.
To check the caller's phone number, use [◀▶] to select *Missed Call* and then press [●] (OK). You can then return the call (see page 17).

Returning a Call (Outgoing History/ Incoming History)

Example: Returning a call to a phone number in the incoming history

When the standby screen is displayed, press ◀.

- Press ▶ while the standby screen is displayed to display the Outgoing History screen.

➡ Use ↕ to select the phone number you want to call and then press ● (View).

- Press ◀▶ to display the Outgoing History screen.

➡ Press [Call key].

- The cell phone can store up to 30 phone numbers in each of the incoming and outgoing history.

One-ring Calls

What is a One-ring Call?

A one-ring call is a call from an unknown caller that only rings once, causing it to be stored in the incoming history. One-ring calls are often used to get you to return the call, which will connect you to a dating service or some other service that charges you at high rates.

One-ring Indicator

[One-ring icon] indicator on the Incoming History screen indicates you have received a one-ring call (a call rang for three seconds or shorter). Be careful when you return a call to an unknown caller.

Adjusting the Earpiece Volume during a Call

During a call, use ↕.

- ▲: Increases the volume.
- ▼: Decreases the volume.

Turning On Manner Mode

When the standby screen is displayed, hold down [*] for at least one second.

This turns on manner mode, and displays [manner icon], [S] and [V] on the standby screen. This also turns on easy voice memo, which is indicated by [voice memo icon] on the standby screen.

Turning Off Manner Mode

When the standby screen is displayed, hold down [*] for at least one second.

Turning off manner mode causes [manner icon], [S] and [V] to disappear from the standby screen. Easy voice memo is also turned off, which is indicated by [voice memo icon] disappearing from the standby screen.

- Even in manner mode, the cell phone still emits a shutter sound when you take a photo.

Changing the Incoming Ring Tone

When the standby screen is displayed, press ◉.

➡ **Use ✥ to select *Settings* and then press ◉ (Select).**

➡ **Use ⇕ to select *Sound/Vib/Lamp* and then press ◉ (Select).**

➡ **Use ⇕ to select *Incoming Setup* and then press ◉ (Select).**

➡ **Use ⇕ to select *Incoming Call* and then press ◉ (Select).**

➡ **Use ⇕ to select *Melody* and then press ◉ (Select).**

➡ **Use ⇕ to select *Fixed Data* and then press ◉ (Select).**

➡ **Use ⇕ to select the ringtone you want to play and then press ◉ (Select).**

The incoming ring tone is set.

- If you press A (Play), the tone plays.

Adjusting the Incoming Ring Tone Volume

When the standby screen is displayed, press ◉.

➡ **Use ✥ to select *Settings* and then press ◉ (Select).**

➡ **Use ⇕ to select *Sound/Vib/Lamp* and then press ◉ (Select).**

➡ **Use ⇕ to select *Incoming Setup* and then press ◉ (Select).**

➡ **Use ⇕ to select *Incoming Call* and then press ◉ (Select).**

➡ **Use ⇕ to select *Volume* and then press ◉ (Select).**

➡ **Use ⇕ to adjust the volume and then press ◉ (OK).**

- Each press of ⇕ changes the volume one step.

Step up	The ring tone volume gradually increases.
Step down	The ring tone volume gradually decreases.
5 ↕ 1	The ring tone sounds at the set volume.
🔇	The ring tone does not sound.

Making and Answering Calls

Turning On the Easy Voice Memo

When the standby screen is displayed, hold down Clear/メモ for at least one second.

[icon] is displayed on the standby screen.

Turning Off the Easy Voice Memo

When the standby screen is displayed, hold down Clear/メモ for at least one second. The easy voice memo is turned off and [icon] disappears from the standby screen.

- The cell phone can record a maximum of ten messages, each up to 60 seconds long.
- Easy voice memo is a function that automatically answers calls and allows callers to record messages. Use the Answering Service (Voice Mail) when your phone is turned off or when you are in a location where a signal cannot be received.

Playing a Message

If a message is recorded, *Easy Voice Memo* appears on the standby screen.

➡ **Use [key] to select *Easy Voice Memo* and then press ● (OK).**

➡ **Use [key] to select the message you want to play and then press ● (Play).**

- To stop playing the message, press ● (Stop).

Deleting a Message

When the standby screen is displayed, press Clear/メモ.

➡ **Use [key] to select *Easy Voice Memo* and then press ● (Select).**

➡ **Use [key] to select *Easy Voice Memo List* and then press ● (Select).**

➡ **Use [key] to select the message you want to delete and then press [A] (Menu).**

➡ **Use [key] to select *Delete* and then press ● (Select).**

➡ **Use [key] to select *Delete One* and then press ● (Select).**

➡ **Use [key] to select *Yes* and then press ● (OK).**

Character Input

Character Entry Modes

When a character entry screen is displayed, you can select a character entry mode if you press (Char).

Menu Items

漢字 : Kanji conversion mode
Code : Character code mode
アイウ : Double-byte katakana mode
ｱｲｳ : Single-byte katakana mode
ａＡ : Double-byte alphabet mode
aA : Single-byte alphabet mode
１２３ : Double-byte number mode
123 : Single-byte number mode
＄％＆ : Double-byte symbol mode
$%& : Single-byte symbol mode

Use ✥ to select a character entry mode and then press ◉ (OK).

Entering Alphanumeric Characters

You can use the keys [1] to [0] to enter characters.
More than one character is assigned to each key.
The following table shows the key assignment for entering characters.

	Number of Times to Press the Key								
key	1	2	3	4	5	6	7	8	9
[1]	.	@	-	_	/	:	~	1	
[2]	a	b	c	A	B	C	2		
[3]	d	e	f	D	E	F	3		
[4]	g	h	i	G	H	I	4		
[5]	j	k	l	J	K	L	5		
[6]	m	n	o	M	N	O	6		
[7]	p	q	r	s	P	Q	R	S	7
[8]	t	u	v	T	U	V	8		
[9]	w	x	v	z	W	X	Y	Z	9
[0]	0	Inputs symbols							
[*]	Inputs symbols (switches an unconfirmed character between uppercase and lowercase).								
[#]	Adds a line break and displays characters in the opposite order.								

When you change your e-mail address, you cannot use the characters in [shaded cells] for the account name (part of the address to the left of @).

Entering Two or More Characters Assigned to the Same Key

After you enter the first character, press ◔ and then enter the next character.

Deleting Characters

To delete one character at a time, move the cursor to the character you want to delete and then press [Clear/メモ]. To delete all characters to the right of the cursor, hold down [Clear/メモ] for at least one second. If there are no characters to the right of the cursor, holding down [Clear/メモ] will delete all the characters.

Starting a New Line

Press [#].

- Certain functions such as c-mail do not support entering new lines.

Entering E-mail Addresses

E-mail Address Compatible Characters

- Before you enter an e-mail address, switch to the single-byte alphabet mode.
- When changing your e-mail address, you can enter up to 30 single-byte alphanumeric and symbol characters for the account name (part to the left of @). Note the following:
  - Uppercase characters cannot be used.
  - Period (.) or zero (0) cannot be used as the first character.

How to Enter E-mail Addresses

Example: Entering "taro.23@kddi.co.jp"

Enter "taro.23".

t : Press [8] once.
a: Press [2] once.
r : Press [7] three times.
o: Press [6] three times.
. : Press [1] once.
2: Press [2] once and then [#].
3: Press [3] once and then [#].

➡ Enter "@".

@: Press [1] twice.

➡ Enter "kddi" and then press ◉ (OK).

k: Press [5] twice.
d: Press [3] once and then ◔.
d: Press [3] once.
i : Press [4] three times.

➡ **Press [A] (Menu).**

➡ **Use ↕ to select *Useful Sentence* and then press ● (Select).**

➡ **Use ↕ to select *.co.jp* and then press ● (Select).**

".co.jp" is entered.

Entering Pictograms

When a character entry screen is displayed, press [E].

Each time you press [E], you can change the character by pictogram ⇒ emoticon ⇒ double-byte symbol ⇒ single-byte symbol in order.

➡ **Use ✥ to select the pictogram you want to enter and then press ● (Select).**

- You can enter pictograms consecutively if you press [A] (Repeat) instead of ● (Select).

Phone Book

Saving a Phone Book Entry

When the standby screen is displayed, hold down [Book] for at least one second.

➡ **Use [Nav] to select [NAME icon] *[Name]* and then press ◉ (Edit).**

➡ **Enter a name and then press ◉ (OK).**
The [READ icon] *[Reading]* for the name is entered automatically.

➡ **Use [Nav] to select [Tel icon] *[Tel. #1]* and then press ◉ (Edit).**

➡ **Enter a phone number and then press ◉ (OK).**
- If the phone number is for a fixed-line phone, enter the phone number starting with the area code.

➡ **Use [Nav] to select a phone number type and then press ◉ (Select).**
- Follow the next step to enter an e-mail address. If you do not want to enter an e-mail address, press [A] (Reg).

➡ **Use [Nav] to select [Mail icon] *[E-Mail 1]* and then press ◉ (Edit).**

➡ **Enter an e-mail address and then press ◉ (OK).**

➡ **Use [Nav] to select an e-mail address type and then press ◉ (Select).**

➡ **Press [A] (Reg).**

- The phone book can store up to 1,000 entries.
- The cell phone automatically saves an entry to the lowest available memory number from 000 to 999.
- You can save three phone numbers and three e-mail addresses for each phone book entry.
- You can also assign a group No., and enter birthday, address, and other information.

Dialing from the Phone Book

When the standby screen is displayed, press [Book].

➡ **Use [Nav] to select the entry containing the phone number you want to dial and then press ◉ (Select).**

➡ **Use [Nav] to select the phone number and then press ◉ (Call).**

➡ **Use [Nav] to select *Call* and then press ◉ (Select).**

Editing Phone Book Entries

When the standby screen is displayed, press [Book].

➡ **Select an entry and press ◉ (Select).**

➡ **Press [A] (Menu).**

➡ **Use [Nav] to select *Edit* and then press ◉ (Select).**

➡ **Edit the contents and then press [A] (Reg).**

➡ **Use [Nav] to select *Yes* and then press ◉ (OK).**

Saving a Phone Number from the Incoming or Outgoing History

Example: Saving a phone number from the incoming history to the phone book

When the standby screen is displayed, press ◀ and use ▲▼ to select the phone number you want to save.

➡ **Press 📖 (Reg).**

➡ **Use ▲▼ to select *Reg. New* and then press ● (Select).**

- For details on saving a phone book entry, see page 23.

Phone Book

Pair Function

You can register a maximum of five pair partners you contact often to easily call or send mail.

Registering a Pair Partner

When the standby screen is displayed, press [ペア].

➡ **Use ◀▶ to select a blank screen and then press [A] (Reg).**

➡ **Use ✥ to select a pair partner, press ● (Reg).**

- When registering a phone book entry with multiple phone numbers and e-mail addresses as pair partner, select the phone number and e-mail address to use with the Pair function.

- When you delete a phone book entry registered in the pair partner, the phone book entry is also deleted from the Pair function.

Making a Call to a Pair Partner

When the standby screen is displayed, press [ペア].

➡ **Use ◀▶ to select the person you want to call.**

➡ **Use ▲▼ to select *Call* and then press ● (Select).**

Sending Mail to a Pair Partner

When the standby screen is displayed, press [ペア].

➡ **Use ◀▶ to select the person you want to send mail.**

➡ **Use ▲▼ to select *E-mail* or *C-mail* and then press ● (Select).**

- To create an e-mail message, see "Creating and Sending E-mail Messages" on page 26. To create a c-mail message, see "Creating and Sending C-mail Messages" on page 29.

Mail

Using E-mail

To use e-mail, you need to apply for an EZweb subscription. If you did not apply for an EZweb subscription at the time of purchase, contact an au shop or the au Customer Service Center. Also, before use, you need to configure initial settings.
You can send and receive e-mail with other cell phones that support e-mail, and with PCs. In addition to text messages of up to 5,000 double-byte (or 10,000 single-byte) characters, you can also send photos and movies by e-mail.

- The packet communication charge for sending and receiving e-mail applies to the amount of data sent and received.
- You can send an e-mail message to up to 30 different addresses (includes To/Cc/Bcc, within 640 single-byte characters) at one time. If you turn the *Addr Count Limit* setting *ON*, you can only send to up to five addresses at one time.
- You can send up to 1,000 e-mail messages per day (a message with multiple recipients is counted as more than one message).
- Sending and receiving e-mail messages that include attachment data may take a while.

Creating and Sending E-mail Messages

When the standby screen is displayed, press ✉.

➡ Use ◎ to select *Create New* and then press ◉ (Select).

➡ Use ◎ to select *Address* and then press ◉ (Edit) and then press ◉ (Select).

➡ Use ◎ to select *Address Book* and then press ◉ (Select).

➡ Use ◎ to select a phone book entry and then press ◉ (Select).

➡ Use ◎ to select an address and then press ◉ (Select).

➡ Press 📖 (Fix).

➡ Use ◎ to select *Subject* and then press ◉ (Edit).

➡ Enter a subject and then press ◉ (OK).

- You cannot enter single-byte katakana characters or a new line in a subject.

➡ Use ◎ to select *Body* and then press ◉ (Edit).

➡ Enter text and then press ◉ (OK).

- You cannot enter single-byte katakana characters.

➡ Press 📖 (Send).

Reading Received E-mail Messages

When you receive an e-mail message, *New E-mail* appears on the standby screen.

➡ **Use ◁▷ to select *New E-mail* and then press ● (OK).**

➡ **Press ● (Select).**

- 📧: Indicates a read message.
- ✉: Indicates an unread message.

➡ **Use ⇕ to select the new message and then press ● (View).**

Reading an E-mail Message from the E-mail Menu

When the standby screen is displayed, press ✉ to display the E-mail menu, use ⇕ to select *Inbox* and then press ● (Select).
For subsequent operations, see "Reading Received E-mail Messages" above.

Reading an E-mail Message with an Attached Photo or Movie

Example: Viewing an attached photo

Display the e-mail message that has an attached photo (above).

➡ **Use ⇕ to select the file name and then press ● (Select).**

➡ **Use ⇕ to select the file name and then press ● (Receive).**

➡ **Press ● (Play).**

- Selecting the file name or pressing ● (Receive) may be unnecessary for some files to be displayed, depending on the file size.

Replying to Received E-mail Messages

When the standby screen is displayed, press ✉.

➡ **Use ⇕ to select *Inbox* and then press ● (Select).**

➡ **Press ● (Select).**

➡ **Use ⇕ to select the message you want to reply to and then press ● (View).**

➡ **Press 📖 (Reply).**
"Re:" is prefixed to the subject, and the text of the message is quoted.

➡ **Refer to "Creating and Sending E-mail Messages" (page 26) for subsequent operations.**

Rejecting Spam

Setting mail filters to reject spam is recommended.
The *サポート設定* (Supportive Settings) helps you to set mail filters easily by answering questions that appear on the screen.

Setting Mail Filters

Example: Connecting to *サポート設定* (Supportive Settings)

When the standby screen is displayed, press ✉.

➡ **Use ◯ to select *E-Mail Setup* and then press ◉ (Select).**

➡ **Use ◯ to select *Mail Filter* and then press ◉ (Select).**

➡ **Use ◯ to select *次へ* (Next) and then press ◉ (Select).**

➡ **Use ◯ to select the input box and then press ◉ (Edit).**

➡ **Enter your security code and then press ◉ (OK).**

➡ **Use ◯ to select *送信* (Send) and then press ◉ (Select).**

➡ **Use ◯ to select an item and then press ◉ (Select).**

カンタン設定 (Simple Settings)

サポート設定 (Supportive Settings)	Set the filter by answering questions This is recommended for users who want to configure settings while confirming conditions.
フィルターレベル（高） Filter Level (High)	Shut out all mail from PCs This is recommended for users who only want to send mail to and receive mail from cell phones.
フィルターレベル（中） Filter Level (Medium)	Block unsolicited advertisement, spoof e-mail and mail from specific addresses This is recommended for users bothered by certain senders or spam mail.
フィルターレベル（低） Filter Level (Low)	Block unsolicited advertisement and spoof e-mail This is the minimum level recommended for all users.

- You can also prevent spam by changing your e-mail address. For details on changing your e-mail address, see page 13.

Mail

Using C-mail

C-mail is a service that uses phone numbers as addresses to exchange messages between au cell phones that support c-mail. A c-mail message can contain up to 50 double-byte (or 100 single-byte) characters.

- The c-mail send charge applies when sending c-mail.

C-mail Safety Block

C-mail safety block is a function that allows you to reject c-mails that include URLs (http://△△△, https://△△△) or phone numbers in the c-mail message text.
C-mail safety block is valid by default. Cancel the setting if you want to receive c-mails that include URLs and phone numbers in the message text.

Creating and Sending C-mail Messages

When the standby screen is displayed, hold down ✉ for at least one second.

➡ **Use ◉ to select *Create New* and then press ◉ (Select).**

➡ **Use ◉ to select To and then press ◉ (Edit).**

➡ **Use ◉ to select *Address Book* and then press ◉ (Select).**

➡ **Use ◉ to select a phone book entry and then press ◉ (Select).**

➡ **Use ◉ to select a phone number and then press ◉ (Select).**

➡ **Use ◉ to select 📄 and then press ◉ (Edit).**

➡ **Enter text and then press ◉ (OK).**

➡ **Press 📖 (Send).**

Reading Received C-mail Messages

When you receive a c-mail message, *New C-mail* appears on the standby screen.

➡ **Use ◉ to select *New C-mail* and then press ◉ (OK).**

- 📂: Indicates a read message.
- ✉: Indicates an unread message.

➡ **Use ◉ to select the new message and then press ◉ (View).**

Reading a C-mail Message from the C-mail Menu

When the standby screen is displayed, hold down ✉ for at least one second to display the C-mail menu, use ◉ to select *Inbox* and then press ◉ (Select).
For subsequent operations, see "Reading Received C-mail Messages" above.

Mail


Camera

Your cell phone has a CMOS camera with 1.96 effective megapixels for shooting photos and movies. You can use the self-timer and autofocus.
Shot images can be used for the standby screen, and attached to e-mail messages.


Photo Taking Tips

When taking photos, frame the subject within the display and hold the cell phone steady with both hands to avoid shaking.

Portrait Position



Landscape Position



About Photo Modes

The following modes are available for taking photos.
Wallpaper (240 x 400) is set at the time of purchase.

Mode	Photo Size	Storage Location
W.paper Mode	Wallpaper (240 x 320)	The *Photo Folder* in the Data Folder of the cell phone
	Wallpaper (240 x 400)	
DSC Mode	0.3M (640 x 480)	The *Digicam Folder* in the Data Folder of a microSD memory card*
	1M (1280 x 960)	
	2M (1600 x 1200)	

* When a microSD memory card (commercially available) is not inserted, the files are saved to the Data Folder of the cell phone.

- Take care not to cover the lens and optical sensor with a strap or finger.

Taking a Photo

When the standby screen is displayed, press ◉.

➡ Use ⊙ to select *Photo* and then press ◉ (Select).

The monitor screen appears.

➡ Frame the subject within the display and then press ◉ (Shot).

The shutter clicks, and the preview screen is displayed.

Saving a Photo

Press ◉ (Save) on the preview screen.

- If you do not want to save the photo, press Clear/メモ in the preview screen.

Viewing Photos

When the standby screen is displayed, press ◉.

➡ Use ⊙ to select *Data Folder* and then press ◉ (Select).

➡ Use ⊙ to select *Photo Folder* and then press ◉ (Select).

➡ Use ⊙ to select a folder and then press ◉ (Select).

➡ Use ⊙ to select the photo you want to view and then press ◉ (View).

EZweb

EZweb Subscription Required

EZweb is an information service that allows you to enjoy browsing the Internet on your cell phone. You can also download Chaku-Uta®, news, and other contents from web pages.
To use EZweb, you need to apply for an EZweb subscription. If you did not apply for an EZweb subscription at the time of purchase, contact an au shop or the au Customer Service Center. Also, before use, you need to configure initial settings.


- The packet communication charge for EZweb connection applies to the amount of data sent and received, not to the length of time connected.
- In addition to communication charges, some sites charge for providing information.

Accessing Sites

Viewing the au one Top

You can access EZweb from the au one Top. A variety of useful and fun sites are available on EZweb.
When the standby screen is displayed, press [E], use [↕] to select *au one Top* and then press [●] (Select).

au one Top



キーワード検索機能 (Search by Keyword)
Provides a search function for searching for information by keyword.

カテゴリ(メニューリスト) (Category (Menu List))
Provides a list of various content provider sites.

トップニュース (Top News)
Provides automatic updates of the latest news.

最新オススメ情報 (Latest News)
Introduces up-to-date information concerning entertainment, daily life, etc.

天気・乗換・占い・テレビ・銀行 (Weather, Transportation, Horoscope, TV & Bank)
Provides direct access to these au one services.

買う (Shopping & Auctions)
Provides a list of shopping and auction sites available from your cell phone.

知る (Tips & Tools)
Provides information on sports and stock prices, as well as useful tools such as maps and dictionaries.

楽しむ (Hobbies & Culture)
Provides the latest information, such as games, music, books, hobbies and entertainment.

暮らす (Lifestyle)
Provides travel, restaurant and other lifestyle-oriented information.

集まる (Community)
Provides interesting and useful information that you can use for SNS or blogs.

メール (Mail)
Provides an extra e-mail address that can be used on your PC.

マイページ (My Page)
Provides useful information and tools tailored to your cell phone usage and a large data storage area.

au style
Introduces information and sites that au recommends.

とくする情報 (Valuable Information)
Presents gifts and push information to the EZweb subscriber for free.

auお客さまサポート (au Customer Support)
Provides information about charges, various applications, au online manual and notices from au.

auワンちゃんの部屋 (au Doggy's Room)
Introduces au Doggy.

カンタンアクセス・オープンサイト (Simple Access & Open Site)
Provides easy access and introduces open sites.

災害用伝言板 (Disaster Message Board)
Register and confirm safety information in time of disaster.

ENGLISH
Introduces English sites.

Basic Operations

Use ◎ to select the site you want to access and then press ● (OK).
Press Clear/メモ to return to the previous screen. Hold down Clear/メモ for at least one second to return to the au one Top.

The following describes the basic operations that are available while accessing sites.

Key Operation	Description
電源	Exits EZweb.
◎ (up/down)	Moves the cursor up and down. When there is data available above or below the current screen, scrolls up and down the screen one line at a time.
◎ (left/right)	When there is data available previous or next to the current screen, moves the screen page by page. ◎ (left) : Returns to the previous screen. ◎ (right) : Moves to the next screen.
Clear/メモ	Returns to the previous screen.

Bookmarking Frequently Accessed Pages

When the page you want to bookmark is displayed, press Ⓐ (Browser menu).

➡ Use ◎ to select *New bookmark* and then press ● (Select).

- Some pages cannot be bookmarked.

➡ Press Ⓐ (Reg).

The displayed page is bookmarked, and its title and URL are added to the Bookmark.

- The Bookmark can contain up to 100 titles and URLs.

Viewing Bookmarked Pages

When the standby screen is displayed, press Ⓔ and then use ◎ to select *EZweb*.

➡ Use ◎ to select *Bookmark(s)* and then press ● (Select).

➡ Use ◎ to select the bookmark for the page you want to view and then press ● (Select).

The cell phone connects to the site.

Checking Charges

When the standby screen is displayed, press ◉.

➡ **Use ✥ to select *Settings* and then press ◉ (Select).**

➡ **Use ⇕ to select *Time/Toll/Sub* and then press ◉ (Select).**

➡ **Use ⇕ to select *Inquire Toll* and then press ◉ (Select).**

➡ **Use ⇕ to select *Yes* and then press ◉ (OK).**
- Select the item you want to check and then follow the on-screen instructions.

Downloading Chaku-Uta®

When the standby screen is displayed, press EZ and then use ⇔ to select *EZweb*.

➡ **Use ⇕ to select *au one Top* and then press ◉ (Select).**

➡ **Use ⇕ to select *カテゴリ（メニューリスト）* (Category (Menu List)) and then press ◉ (OK).**

➡ **Use ⇕ to select *着うた* (Chaku-Uta®) and then press ◉ (Select).**

➡ **Use ⇕ to select the site you want to access and then press ◉ (Select).**

The download instructions appear.
- Fee-based information sites require entry of EZ password or Premium EZ password. Follow the on-screen instructions to enter either password. See page 14 for details.

➡ **Follow the on-screen instructions.**

Download is completed.
- Downloaded data is saved automatically to the Data Folder.

➡ **Press 📖 (Play).**

The downloaded Chaku-Uta® plays.


- This procedure is only an example for the purpose of explanation and may differ from actual procedures. Follow the instructions on the site from which you want to download the data.

EZ News Flash

EZweb Subscription Required

Use the EZ News Flash to display flash news on the standby screen. You can check the news details and other information by selecting the ticker field.
You can use the EZ News Flash by making a few simple settings following the EZweb initial setup.

Basic Operations



- The EZ News Flash information is automatically received at no charge. Note, however, that packet communication charges may be incurred for manual updates and connecting to EZweb sites. In this case, a confirmation screen for network connection is displayed.
- The EZ News Flash information is updated at regular time intervals. [icon] appears while receiving information.

Setting EZ News Flash

The EZ News Flash is available free of charge. You have only to make a few simple settings. After following the procedure in “Initial Setup of E-mail and EZweb” on page 10, configure EZ News Flash settings. If you did not configure the EZ News Flash settings at the time of the initial setup, follow the steps below.

When the standby screen is displayed, select the ticker field and then press ◉ (OK).

➡ Follow the on-screen instructions.

The setup procedure is completed.

- When the standby screen returns, a message asking you to wait for a while until the next update takes place appears in the ticker field.

Canceling EZ News Flash

When the standby screen is displayed, select the ticker field and then press ◉ (OK).

➡ Press Ⓐ (メニュー[Menu]), use ⇕ to select *サービス設定解除* (Service Cancellation) and then press ◉ (選択[Select]).

➡ Follow the on-screen instructions.

Changing the Reception Settings for EZ News Flash Information

You can change the ring tone, vibrator and LED settings under M215 *News Flash Rcv.* for reception of EZ News Flash information.

If you do not want the ring tone to sound when receiving EZ News Flash information, set the volume to *Level 0*.

EZ Navi

EZweb Subscription Required

Using GPS (Global Positioning System), EZ Navi provides useful positional information services.

When the standby screen is displayed, press [EZ] and then use [◀▶] to select the *EZnavi*.

- The packet communication charges for using EZ Navi services apply to the amount of data sent and received. Some services may require a separate information fee.
- Before using EZ Navi, you must configure initial settings of EZweb (page 10).

Passenger Seat Navi for People in the Passenger Seat to Check the Route

Passenger Seat Navi guides the passengers to the destination with the best route using voice and map.

Drivers are not allowed to use Passenger Seat Navi.

Security Navi to Check Where Your Kids Are

The Security Navi application is made up of the following three functions:
いつでも位置確認 (Auto Position Search [monthly charge]),
エリア通知 (Area Message [no monthly charge]),
位置確認メール (Position Search Mail [no monthly charge])

Using these functions, you can check the position of an au cell phone that supports Security Navi; and automatically send a mail notification to the specified au cell phones when you enter (or are in) or leave (or are no longer in) the set area within a predetermined period of time.

EZ Navi Walk for When You Go Out

NS02 has two modes of EZ Navi Walk menu. You can use all functions of EZ Navi Walk in the Full mode, and you can use the basic functions easily in the Simple mode. The Simple mode is set at the time of purchase. You can change the two modes by pressing [EZ] on the EZ Navi Walk menu screen.

Full mode

トータルナビ／地図	Find the best route by various transportation such as train, airplane, bus, taxi and so on. Check out maps of your current location and place you like to go.
乗換／時刻表	Search for train connections, timetables and other public transportation information.
お店／施設／イベント	Search for local stores, facilities or events.
ドライブ／渋滞情報	Check out information on roads and traffic jams throughout Japan in real time.
おススメ便利メニュー	View information on services that are available on PCs.
設定／会員登録／インフォ	Configure various settings. Sign up as a member. View information on campaigns.

Simple mode

ナビをする	Find the best route by various transportation such as train, airplane, bus, taxi and so on.
現在地の地図	Check out maps of your current location.
乗換案内	Search for train connections.
渋滞／交通情報	Check out information on roads and traffic jams throughout Japan in real time.
会員登録・インフォ	Configure various settings. Sign up as a member. View information on campaigns.
フルモードとは	Introduce the functions of the Full mode.

- Some of the menu options require a monthly charge.


The Map of Your Current Location



★ represents your initial location. As you start moving, changes of your location are tracked by continuous positioning and indicated in real time by [icon].

The *現在地の地図* (The Map of Your Current Location) option displays the current map in real time.

3D Navi



Navigation engine by NAVITIME JAPAN
Map: Shobunsha Publications, Inc.
©2008 ZENRIN CO., LTD
Geographical Survey Institute
3D data: ©2008 ZENRIN CO., LTD
GEO Technical Laboratory co., Ltd.
Z06A-No.2137

Shows a 3D view at guidance points and around the destination area.
You can use 3D Navi only in the Full mode.

Evacuate Navi to Guide You Home or to Nearby Evacuation Areas during Disasters

Nearby public evacuation areas or the direction to your home can be determined using the map data pre-installed on the NS02 (*避難所マップ*[Evacuate Area Map]).
Other useful contents can be downloaded from the *災害時ナビ*(Evacuate Navi) section of the EZweb site, including *帰宅支援マップ*(Route Home Map) which can guide you between two locations you specify, for example, from your office to home.

- Some contents require a monthly charge.
- Use the information on the screen as a reference and always follow the instructions of police, fire and other municipal authorities.
- When using Evacuate Navi, checking your current position may take more time than usual depending on the status of the GPS satellites.

In Case of Loss of Your NS02

The Remote Auto Lock allows you to remotely activate the Auto Lock, and Address Book Lock, preventing others from using your cell phone.

Setting Conditions for Activating the Remote Auto Lock

You can activate the Remote Auto Lock by calling your NS02 a set number of times from a registered phone number within a specified period of time.

When the standby screen is displayed, press ◉.

➡ **Use ✣ to select *Settings* and then press ◉ (Select).**

➡ **Use ⇕ to select *Privacy Setup* and then press ◉ (Select).**

➡ **Use ⇕ to select *Security Lock* and then press ◉ (Select).**

➡ **Use ⇕ to select *Remote Auto Lock* and then press ◉ (Select).**

➡ **Enter Lock No., and then press ◉ (OK).**

➡ **Use ⇕ to select *Caller ID List* and then press ◉ (Select).**

➡ **Press ◉ (Edit).**

➡ **Enter a phone number, and then press ◉ (Reg).**

➡ **Press 📖 (Back).**

➡ **Use ⇕ to select *Specified Time* and then press ◉ (Select).**

➡ **Enter a time and then press ◉ (OK).**

- This sets the time limit for receiving the set number of calls after the first call is received.
- You can set a time from one to ten minutes.

➡ **Use ⇕ to select *Incoming Call Count* and then press ◉ (Select).**

➡ **Enter a number of calls, and then press ◉ (OK).**

- This sets the number of calls to receive to activate the Remote Auto Lock.
- You can set a number of calls from three to ten.

➡ **Use ⇕ to select *ON/OFF Setup* and then press ◉ (Select).**

➡ **Use ⇕ to select *ON* and then press ◉ (OK).**

Remotely Activating the Remote Auto Lock on Your NS02

Call the NS02 from the registered phone number repeatedly within the set time limit.

- When the specified number of calls are received, the Remote Auto Lock is activated and a message plays telling you that the cell phone is locked.

Activating the Remote Auto Lock by the Security Lock Service

Even if the Remote Auto Lock is not set in advance, the Remote Auto Lock can be activated by calling au Customer Service Center or completing the application process on au Customer Support from a PC.
The Security Lock Service is available free of charge.

Calling au Customer Service Center to Activating/Canceling the Remote Auto Lock

From an au cell phone: 113 without a prefix (toll free)
From any other cell phone or fixed-line phone:
0077-7-113 (toll free)
Open 24 hours

Follow the voice guidance to complete the application process.

Activating/Canceling the Remote Auto Lock from a PC

Login to au Customer Support (http://cs.kddi.com/) and complete the application process by following the on-screen instructions.

- The Remote Auto Lock cannot be activated when the NS02 is turned off or out of the service area, or Emission OFF is set to ON.

- You must fill out an application to use au Customer Support (the application can be filled out even after your cell phone is lost).

Troubleshooting

Symptom	Possible Cause	Remedy	Page
Cannot turn on power.	● Is the battery pack charged?	Charge the battery pack.	8
	● Did you hold down [電源] for at least one second?	Hold down [電源] for at least one second.	10
Cannot make calls.	● Is power turned on?	Hold down [電源] for at least one second.	10
	● Is [圏外] (out of range indicator) displayed?	Move to a location where [圏外] (out of range indicator) is no longer displayed, and try again.	10
	● Is your hand or a metal object covering the area around the built-in antenna?	Make sure your hand or any other metal object is not covering the area around the built-in antenna.	7
	● Did you enter the phone number starting with the area code?	When making a call to a phone other than a cell phone, you need to enter the area code even if you are inside the same area.	15
Cannot receive calls.	● Is [圏外] (out of range indicator) displayed?	Move to a location where [圏外] (out of range indicator) is no longer displayed.	10
	● Is power turned on?	Hold down [電源] for at least one second.	10
No response when a key is pressed.	● Is power turned on?	Hold down [電源] for at least one second.	10
A warning tone sounds and power turns off.	● Is there enough power left in the battery pack?	Charge the battery pack.	8
Calls are answered automatically.	● Is easy voice memo turned on?	Hold down [Clear/メモ] for at least one second to turn off easy voice memo.	19

Symptom	Possible Cause	Remedy	Page
Cannot hear the other party.	● Is the earpiece volume too low?	Press ⓘ during a call to increase the earpiece volume.	17
When making a call, a beeping sound is heard from the earpiece and a connection cannot be established.	● Is 圏外 (out of range indicator) displayed? Or are you in a location where the signal is too weak?	Move to a location where 圏外 (out of range indicator) is no longer displayed.	10
	● Is the wireless line busy or is the phone you are calling on another line?	End the call and try again later.	15
The incoming indicator flashes but the ring tone does not play.	● Is manner mode turned on?	Hold down [*] for at least one second to turn off manner mode.	17
	● Is [S] (ring tone off indicator) displayed?	Increase the volume of the incoming call ring tone.	18
Cannot charge the battery pack.	● Is the cell phone inserted in the desktop holder (sold separately) properly?	Insert the cell phone in the desktop holder (sold separately) properly.	8
	● Are the plug and connector of the Pantech external terminal conversion adapter 02 and common AC adapter 01/02 (sold separately) inserted properly?	Insert the plug and connector firmly.	
When the camera is activated, no subject is displayed.	● Is a finger or other object covering the camera (lens)?	Check the position of the camera (lens) and remove the obstacle.	30

- For more detailed information, visit the following au troubleshooting sites:
  - From an au cell phone: [EZ] ⇒ *au one Top* ⇒ *auお客さまサポート* (au Customer Support) ⇒ *オンラインマニュアル* (Online Manual) ⇒ *故障診断Q&A* (Troubleshooting FAQ)
  - From a PC: http://www.kddi.com/customer/service/au/trouble/kosho/index.html

Index

A

B

C

D

E

I

K

L

M

N

O

P

For inquiries, call: au Customer Service Center

For general information and charges (toll free)

From fixed-line phones: 0077-7-111

From au cellphones: 157 area code not required

PRESSING ZERO WILL CONNECT YOU TO AN OPERATOR
AFTER CALLING 157 ON YOUR au CELLPHONE

For loss, theft or damage and operation information (toll free)

From fixed-line phones: 0077-7-113

From au cellphones: 113 area code not required

From EZweb:

Access Method EZ▶au one Top▶auお客さまサポート (au Customer Support)▶お問い合わせ (Inquiries)

・ Menus are subject to change without prior notice.

なるほど! au
みんなでつくる、auQ&Aサイト

Access Method EZ▶au one Top▶auお客さまサポート (au Customer Support)▶みんなでQ&A「なるほど!au」

Read this code for an easy access to なるほど! au (au User's Forum). ▶

• The packet communication charge applies.

Cellphone and PHS operators collect and recycle unused telephones, batteries and battery chargers at stores bearing the logo regardless of brand and manufacturer to protect the environment and reuse valuable resources.

モバイル・リサイクル・ネットワーク
携帯電話・PHSのリサイクルにご協力を。

Read this code for an easy access to au Online Manual.

February 2009, 1st Edition

Sales: KDDI CORPORATION・
OKINAWA CELLULAR TELEPHONE COMPANY
Manufactured by: Pantech&Curitel Communications, Inc.